



# Quality Checklist

123 SW 12th Street • Loveland, Colorado 80537 USA • +1-970-377-1111  
[www.lulzbot.com](http://www.lulzbot.com)

---

Model: TAZ 3D Printer

Serial Number: \_\_\_\_\_

Date Checked: \_\_\_\_\_

Checked by: \_\_\_\_\_

## General

- Are all the screws and zip ties tight?
- Are the X and Y axis square to each other?
- Are the gaps at the ends of the extrusion closed?
- Are all the parts flush and straight to the edges with clean lines?
- Are the current version of parts being used?
- Do the bed & x-carriage zip ties stop the wires from sliding in and out?
- Verify that the following are mounted correctly:
  1. Feed tube, tube on back side of mount
  2. Spool mount, correct height
  3. Y axis, correct location in X and Y directions
  4. Double bearing on carriage, step side towards X motor
  5. Finger clip, taller side on left
- Are the switches tight? Do they wiggle side to side?
- Are the switches flush or above the mounts?
- Are all 8 rubber feet installed?
- Does the outer spool holder slide in the inner spool holder smoothly?
- Is the PET tape free of bubbles and wrinkles?
- Is the heat bed adhesive smooth and consistent with no finger prints?
- Does the extruder mount have 4 unused inserts on the sides?
- Does filament slide through the feed tube?



# Quality Checklist

123 SW 12th Street • Loveland, Colorado 80537 USA • +1-970-377-1111  
[www.lulzbot.com](http://www.lulzbot.com)

---

## Y Axis

- Does the Y bed move freely back and forth?
- Is the Y bed tight side to side from motion and twisting?
- Are all the screws on the bearing holders tight?
- Does the Y belt rub the bottom of the y-idler by the bearings?
- Is the Y pulley tight?
- Is one one of the set screws on the Y pulley aligned with the flat on the motor shaft?
- Is the level of the Y pulley at the same height as where the belt mounts on the belt holder?
- Is the Y belt tight?
- Are the bed leveling springs/posts in the correct place?
- Are all the Y mounting brackets flush and tight?
- Are the Y bars approximately 4mm inside of the end plates?
- Are the belts trimmed far enough to not interfere with the pulley or bearing?

## X Axis

- Is the X pulley tight?
- Is one one of the set screws on the X pulley aligned with the flat on the motor shaft?
- Is the X pulley far enough out so the belt doesn't rub on the screw heads on the x-carriage?
- Are the pulleys and clamps adjusted so the X belt does not rub the X idler at all?
- Is the X belt tight?
- Does the X axis move freely end to end?
- Are the X bars flush with the left side?
- Are the screws that hold the X bars tight?
- Are the belts trimmed far enough to not interfere with the pulley or bearing?



# Quality Checklist

123 SW 12th Street • Loveland, Colorado 80537 USA • +1-970-377-1111  
[www.lulzbot.com](http://www.lulzbot.com)

---

## Z Axis

- Is there a washer under the Z adjustment spring
- Is the Z adjuster vertical?
- Are the coupler zip ties tight. Do vertical pull test.
- Are the Z nut holders oriented correctly with the spring under the nut?
- Are the Z bars flush with the top plate?
- Are the drive rods straight?
- Have the drive rods been lubricated?

## Extruder

- Can you adjust the extruder springs?
- Are the V grooves on the extruder gears lined up?
- Is the extruder mount secure on the x-carriage?
- Does the idler bearing stick out of the idler block?
- Is the hobbing aligned to the hole in the extruder?
- Is the set screw in the small gear tight and on the flat of the motor shaft?
- Can you feed filament about 115mm from the top of the extruder?
- Are the gears tight with no back-lash?
- Do the extruder gears turn smoothly for several rotations?

## Electronics (leave cover off until inspected)

- Are the screw terminals tight with no insulation inside the clamp?
- Are the RAMBo board, switch and plugs wired correctly?
- Are the quick disconnect terminals pushed all the way onto the switch?
- Can you plug in USB cable from the outside of the enclosure?
- Is the fan mounted on the cover correctly?
- Are the motor extension ground wires secured to the case?